

## Specifications

LED Replacement is approximately 1/2 of the CFL wattages. Adapter will add .25" - .50" to overall length

	PART #	FIXTURE SOCKET	LAMP TYPE	RATING	SOCKET	LAMP
	Adapter-1	Candelabra (E11)	Medium (E26)	125v/0.8A	Candelabra	Medium
	Adapter-2	Intermediate (E17)	E12	250v/4A	Intermediate	Candelabra
	Adapter-3	Intermediate (E17)	Medium (E26)	125v/0.8A	Intermediate	Medium
	Adapter-4	Double Contact (Bayonette)	Medium (E26)	125v/0.8A	Double Bayonette	Medium
	Adapter-5	Medium (E26) Extender	Medium (E26)	250v/4A	Medium	Medium (Extender), adds 1.25" to length
	Adapter-6	Medium (E26)	Mogul (E39)	250v/4A	Medium	Mogul
	Adapter-7A (Ceramic)	Mogul (E39)	Medium (E26)	250v/4A	Mogul	Medium
	Adapter-7 (Plastic)	Mogul (E39)	Medium (E26)	250v/4A	Mogul	Medium
	Adapter-8	Mogul (E39) No Extra Length	Medium (E26)	250v/4A	Mogul	Medium, no extra length
	Adapter-9	Mogul (E39) Extender	Mogul (E39)	660v/6A	Mogul	Mogul (Extender), adds 1.25" to length
	Adapter-10	GU24	Medium (E26)	250v/6A	GU24	Medium
	Adapter-11	G24D (1/2/3)	Medium (E26)	250v/2.5A	G24D (1/2/3)	Medium
	Adapter-11-B	G24D (1/2/3)	Medium (E26)	250v/2.5A	G24D (1/2/3)	Medium
	Adapter-12	G24Q (1/2/3) GX24Q (1/2/3/4/5)	Medium (E26)	250v/2.5A	G24Q (1/2/3)	Medium, also replaces GX24Q (1/2/3/4/5)
	Adapter-13	GX23 (1/2/3)	Medium (E26)	250v/2.5A	GX23 (1/2/3)	Medium
	Adapter-14	G23 Medium	Medium (E26)	250v/2.5A	G23 Medium	Medium
	Adapter-15	Mogul (EX39) Pulse Start	Mogul (E39)	250v/4A	Pulse Start Mogul	Mogul
	Adapter-16	Medium (E26) Extender	Medium (E26)	250v/0.8A	Medium	Medium (Extender) for 4 K.V. pulse rated socket, adds 1.25" to length
	Adapter-17	Double Contact (Sox)	Mogul (E39)	250v/0.8A	Double contact (Sox)	Mogul
	Adapter-18	Medium (E26)	Candelabra (E12)	250v/0.8A	Medium	Candelabra
	Adapter-19	Medium (E26) Extender	Medium (E26)	250v/4A	Medium	Medium (Extender), adds 2.50" to length